

HEX-O 500

suspended group
073-6351638P



Project / Type
Notes
Count / Date



RG0 IEC 62471	220-240V	X-PERT	X-PERT
------------------	----------	--------	--------

General

Ceiling , Suspended
black , RAL9005 ¹
IP20
2060 lm

LED

4000 K
CRI ≥ 80
L90 / 50000 h
photobio. safety RG 0 - no Risk
initial MacAdam ≤ 3 SDCM
MR 0.72
MDER 0.66

Optical

Microprismatic
microprismatic
UGR < 19 , ≥65° <3000 cd/m ²
PstLM ≤ 1.0 ²
SVM ≤ 0.4 ²

Electrical


DALI-2
system 16.3 W
PC1 220-240V
system 126 lm/W ³
1 DALI Addr.

Physical


cable 1500 mm (min. 500 mm)
length 500 mm
width 433 mm
height 100 mm
5.5 kg

Hexagonal light fitting from aluminium profile; seamlessly welded; surface black powder coated; pendant fitting with 1500mm cable suspension (1 cable); height adjustment without tools; canopy with 2 cable openings and plug-in terminal for through wiring, incl. feed available as an accessory; suitable for group installation; including rear rail for alignment of the housings; can be combined with all HEX-O ceiling and TRIG-O ceiling luminaires and acoustic elements; highly reflective coating for improved efficiency; microprismatic PMMA cover; completely homogeneous illumination; same luminance for all size versions; UGR ≤ 19; VDU compatible workplace luminaire according to DIN EN 12464-1; luminance above 65° ≤ 3000 cd/m²; light colour 4000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 80; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; degree of protection IP20; PC1 220-240V; photobiological safety according to IEC 62471 risk group RG 0 - no Risk; internal wiring in light halogen free; incl. DALI-2 converter; sound absorbing HEX-O ABSORBER available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



¹ RAL code ² Value of containing product at full load (undimmed)
³ incl. optical losses and the efficiency of the operating device (converter)

Installation instructions



Lighting calculator

