

LENO microprismatic

trimless

051-8316537G



Project / Type

Notes

Count / Date



RG0
IEC 62471

220-240V

↑ IP20
↓ IP40

General

Ceiling / Wall , Recessed

white , RAL9016 ¹

1900 lm/m

front IP40 , back IP20

3480 lm

LED

3000 K

CRI ≥ 80

L90 / 50000 h

photobio. safety RG 0 - no Risk

initial MacAdam ≤ 3 SDCM

MR 0.54

MDER 0.49

Optical

Microprismatic

microprismatic

UGR < 19

PstLM ≤ 1.0 ²

SVM ≤ 0.4 ²

Electrical

DALI-2

system 28.6 W

PC2 220-240V

system 122 lm/W³

1 DALI Addr.

16 W/m

Physical

trimless

length 1833 mm

width 92 mm

height 13 mm

3.9 kg

Cutout

length 1836 mm

width 95 mm

min. ceiling thickness 12.5 mm


max. ceiling thickness 25 mm

recessed depth 58 mm


recessed depth: 12.5 mm (ceiling) + 45 mm (converter)

Low profile recessed channel, height 13 mm; suitable for rimless installation in 12.5mm plasterboard ceilings; specially designed trim with grooves for better adhesion of smoothing compound; suitable for wall or ceiling mounting; surface white powder coated; easy mountng without need to cut the substructure; fall-safe light inset made of extruded aluminium profile, can be inserted in the canal without tools by magnetic holders; side coupled light directed downward through LGP (LIGHT GUIDING PRISM) body and high efficiency reflector; micro prismatic PMMA diffuser incl. diffuser film for homogeneous illumination and reduced luminance; UGR ≤ 19; light colour 3000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 80; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; degree of protection from below IP40 (from above IP20); PC2 220-240V; photobiological safety according to IEC 62471 risk group RG 0 - no Risk; internal wiring in light halogen free; incl. external converter for ceiling insertion; DALI-2 control; light source not replaceable; control gear replaceable by an authorized professional;

Light distribution



Product drawing



¹ RAL code ² Value of containing product at full load (undimmed)
³ incl. optical losses and the efficiency of the operating device (converter)

Installation instructions

