

# SASSO 100 round downlight trim soft acoustic ceiling

048-2700217X 048-2796397 002-90766



Project / Type	
Notes	
Count / Date	



--	--	--

### General

Ceiling , Recessed
white , RAL9016 <sup>1</sup>
Signal white
front IP44 , back IP20
1620 lm

### LED

3500 K
CRI ≥ 90
L80 / 50000 h
initial MacAdam ≤ 2 SDCM
R <sub>g</sub> : 99 , R <sub>r</sub> : 90 , R <sub>t1-15</sub> : 89
MR 0.7
MDER 0.64

### Optical

super wide flood
beam angle 69°
PstLM ≤ 1.0 <sup>2</sup>
SVM ≤ 0.4 <sup>2</sup>

### Electrical

non DIM
system 17.9 W
inset 15.2 W
36 Vf
450 mA
PC2 220-240V
system 91 lm/W <sup>3</sup>
inset 106 lm/W <sup>4</sup>

### Physical


with trim for acoustic ceiling
diameter 114 mm
height 75 mm
0.46 kg

### Cutout


diameter 100 mm
min. ceiling thickness 25 mm
max. ceiling thickness 40 mm
recessed depth 80 mm

Round recessed spotlight in die-cast aluminium; 1 lamp; surface white; installation without tools in mounting set due to patented ball catch system; round installation housing; with trim Signal white; for installation in soft acoustic ceilings; suitable for ceiling thickness of 25-40 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 3500 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 69° beam; degree of protection from below IP44 (from above IP20); PC2 220-240V; incl. converter, non dimmable; through wiring connection box, 3-pole or 5-pole, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

### Light distribution



### Product drawing



<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)  
<sup>3</sup> incl. optical losses and the efficiency of the operating device (converter)  
<sup>4</sup> incl. optical losses

### Installation instructions



### Lighting calculator

