

# BO 55

track

180-7312617S



Project / Type

Notes

Count / Date



## General

Ceiling , Track

tilt max 90°

rotation 355°

white , RAL 9016 <sup>1</sup>

IP20

2320 lm

## LED

4000 K

CRI ≥ 90

L80 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 98 , R<sub>f</sub>: 90 , R<sub>t(1-15)</sub>: 88

MR 0.8

MDER 0.72

## Optical

spot

beam angle 17°

## Electrical

non DIM

220-240 V

system 22.3 W

system 104 lm/W<sup>2</sup>

PC2

## Physical


diameter 55 mm

height 140 mm

0.5 kg

Cylindrical tracked spotlight in die-cast aluminium with 3PH universal adapter; classic style in elegant design for discerning requirements; surface white powder coated; 355° rotatable and 90° tiltable; converter integrated in the power track adapter; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 4000 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; high quality, aluminium, vapour deposition coated reflector with faceted lens design; precise radiation characteristic with 17° beam; good glare control through recessed light point level; optical attachment available as accessory; accessories are listed separately; degree of protection IP20; PC2; 220-240 V; adapter for toolless insertion or movement on a variety of 3-phase power tracks; incl. converter, non dimmable; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;


## Light distribution



spot 17°

| h (m) | EO° (lx) | ø (m) |
|-------|----------|-------|
| 1     | 16200    | 0.29  |
| 2     | 4000     | 0.58  |
| 3     | 1800     | 0.87  |
| 4     | 1000     | 1.16  |
| 5     | 600      | 1.45  |

## Product drawing



<sup>1</sup> RAL code

<sup>2</sup> FIXTURE: incl. consideration of optical losses & internal control unit losses SYSTEM: incl. consideration of optical losses, internal control unit losses & operating device efficiency.

## Installation instructions



## Lighting calculator

