



Project / Type

Notes

Count / Date



General

Ceiling , Track

tilt max 310°

rotation 360°

white , RAL 9016 ¹

IP20

343 lm

LED

4000 K

CRI ≥ 95

L90 / 50000 h

initial MacAdam ≤ 2 SDCM

R_g: 98 , R_f: 91 , R₍₁₋₁₅₎: 95

MR 0.85

MDER 0.77

Optical

framing


beam angle 32°

PstLM ≤ 1.0 ²

SVM ≤ 0.4 ²

Track light made of die-cast aluminium; surface white powder coated; 360° rotatable and 310° tiltable; converter installed in aluminium spotlight housing; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 4000 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 95; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; contoured spotlight for precise circular shape; easy adjustment by iris-shaped shielding device made of stainless steel; including high quality bi-convex glass lens; sharp object focusing through adjustable lens; focusing by means of rubberised adjusting ring on the spotlight head; degree of protection IP20; PC1; 220-240 V; adapter for toolless insertion or movement on a variety of 3-phase power tracks; adapter fixation without tools by means of knurled screw; incl. DALI-2 converter; point outlet, either in surface mounted housing or recessed housing, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;


Light distribution



framing 32°

h (m)	E0° (lx)	ø (m)
1	1380	0.57
2	340	1.13
3	150	1.70
4	90	2.26
5	60	2.83

Product drawing



Electrical

DALI-2

220-240 V

system 23.0 W

system 15 lm/W³

PC1

1 DALI Addr.

Physical

diameter 70 mm

height 156 mm

1 kg

tool-free fixation

¹ RAL code ² Value of containing product at full load (undimmed)
³ FIXTURE: incl. consideration of optical losses & internal control unit losses SYSTEM: incl. consideration of optical losses, internal control unit losses & operating device efficiency.

Installation instructions



Lighting calculator

