

# BO 45

intrack  
180-7211617V



Project / Type \_\_\_\_\_


Notes \_\_\_\_\_

Count / Date \_\_\_\_\_



Cylindrical tracked spotlight in die-cast aluminium with 3PH universal adapter; classic style in elegant design for discerning requirements; surface white powder coated; 360° rotatable and 90° tiltable; converter integrated in the power track adapter; passive cooling of the LEDs through improved heat sink geometry; with high power LED for maximum efficiency; no appearance of multiple shadows; light colour 4000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 90; min. 85% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 8° beam; good glare control through recessed light point level; optical attachment available as accessory; accessories are listed separately; degree of protection IP20; PC2 220-240V; adapter for toolless insertion or movement on a variety of 3-phase power tracks; adapter flush with the power track; incl. converter, non dimmable; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;


## Light distribution



super spot 8°

h (m)	EO° (lx)	ø (m)
1	13000	0.14
2	3200	0.28
3	1400	0.41
4	800	0.55
5	500	0.69

## Product drawing



## General

Ceiling , Track \_\_\_\_\_

tilt max 90° \_\_\_\_\_

rotation 360° \_\_\_\_\_

white , RAL9016 <sup>1</sup> \_\_\_\_\_

IP20 \_\_\_\_\_

371 lm \_\_\_\_\_

## LED

4000 K \_\_\_\_\_

CRI ≥ 90 \_\_\_\_\_

L85 / 50000 h \_\_\_\_\_

initial MacAdam ≤ 3 SDCM \_\_\_\_\_

R<sub>g</sub>: 94 , R<sub>f</sub>: 87 , R<sub>(1-15)</sub>: 90 \_\_\_\_\_

MR 0.86 \_\_\_\_\_

MDER 0.78 \_\_\_\_\_

## Optical

super spot \_\_\_\_\_

beam angle 8° \_\_\_\_\_

## Electrical

non DIM \_\_\_\_\_

system 9.3 W \_\_\_\_\_

PC2 220-240V \_\_\_\_\_

system 40 lm/W<sup>2</sup> \_\_\_\_\_

## Physical

diameter 45 mm \_\_\_\_\_

height 120 mm \_\_\_\_\_

0.3 kg \_\_\_\_\_

<sup>1</sup> RAL code  
<sup>2</sup> incl. optical losses and the efficiency of the operating device (converter)

## Installation instructions



## Lighting calculator

