



Project / Type _____

Notes _____

Count / Date _____



General

Ceiling , Track _____

tilt max 310° _____

rotation 360° _____

black , RAL9005 ¹ _____

IP20 _____

231 lm _____

LED

4000 K _____

CRI ≥ 95 _____

L90 / 50000 h _____

initial MacAdam ≤ 2 SDCM _____

R_g: 98 , R_f: 91 , R₍₁₋₁₅₎: 95 _____

MR 0.85 _____

MDER 0.77 _____

Optical

framing _____


beam angle 32° _____

PstLM ≤ 1.0 ² _____

SVM ≤ 0.4 ² _____

Track light made of die-cast aluminium; surface black powder coated; 360° rotatable and 310° tiltable; converter installed in aluminium spotlight housing; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 4000 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 95; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; contoured spotlight for precise circular shape; easy adjustment by iris-shaped shielding device made of stainless steel; including high quality bi-convex glass lens; sharp object focusing through adjustable lens; focusing by means of rubberised adjusting ring on the spotlight head; degree of protection IP20; PC1 220-240V; adapter for toolless insertion or movement on a variety of 3-phase power tracks; adapter fixation by means of set screw; incl. DALI-2 converter; point outlet, either in surface mounted housing or recessed housing, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;


Light distribution



framing 32°

h (m)	E0° (lx)	ø (m)
1	929	0.57
2	232	1.13
3	103	1.70
4	58	2.26
5	37	2.83

Product drawing



Electrical

DALI-2 _____

system 14.0 W _____

PC1 220-240V _____

system 17 lm/W³ _____

inset 19 lm/W⁴ _____

1 DALI Addr. _____

Physical

diameter 70 mm _____

height 156 mm _____

1 kg _____

set screw (tool required) _____

¹ RAL code ² Value of containing product at full load (undimmed)
³ incl. optical losses and the efficiency of the operating device (converter)
⁴ incl. optical losses

Installation instructions

Lighting calculator