



Project / Type

Notes

Count / Date



**General**

Ceiling , Track

tilt max 310°

rotation 360°

white , RAL9016 <sup>1</sup>

IP20

210 lm

**LED**

3000 K

CRI ≥ 95

L90 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 99 , R<sub>f</sub>: 94 , R<sub>(1-15)</sub>: 96

MR 0.66

MDER 0.6

**Optical**

framing

beam angle 32°

PstLM ≤ 1.0 <sup>2</sup>

SVM ≤ 0.4 <sup>2</sup>

Track light made of die-cast aluminium; surface white powder coated; 360° rotatable and 310° tiltable; converter installed in aluminium spotlight housing; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 3000 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 95; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; contoured spotlight for precise circular shape; easy adjustment by iris-shaped shielding device made of stainless steel; including high quality bi-convex glass lens; sharp object focusing through adjustable lens; focusing by means of rubberised adjusting ring on the spotlight head; degree of protection IP20; PC1 220-240V; adapter for toolless insertion or movement on a variety of 3-phase power tracks; adapter fixation by means of set screw; incl. converter, dimmable with integrated potentiometer; point outlet, either in surface mounted housing or recessed housing, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

**Electrical**

DIM POTI

system 14.0 W

PC1 220-240V

system 15 lm/W<sup>3</sup>

inset 18 lm/W<sup>4</sup>

**Physical**


diameter 70 mm

height 156 mm

1 kg

set screw (tool required)


Light distribution



framing 32°

h (m)	E0° (lx)	ø (m)
1	844	0.57
2	211	1.13
3	94	1.70
4	53	2.26
5	34	2.83

Product drawing



<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)  
<sup>3</sup> incl. optical losses and the efficiency of the operating device (converter)  
<sup>4</sup> incl. optical losses

**Installation instructions**

**Lighting calculator**