



Project / Type

Notes

Count / Date



General

Ceiling , Track

tilt max 310°

rotation 360°

black , RAL9005 <sup>1</sup>

IP20

1460 lm

LED

3000 K

CRI ≥ 95

L90 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 99 , R<sub>f</sub>: 94 , R<sub>t(1-15)</sub>: 96

MR 0.66

MDER 0.6

Optical

spot

beam angle 12°

PstLM ≤ 1.0 <sup>2</sup>

SVM ≤ 0.4 <sup>2</sup>

Electrical

DALI-2

system 22.9 W

PC1 220-240V

system 64 lm/W<sup>3</sup>

inset 75 lm/W<sup>4</sup>

1 DALI Addr.

Physical

diameter 70 mm


height 98 mm

0.9 kg

set screw (tool required)

Track light made of die-cast aluminium; surface black powder coated; 360° rotatable and 310° tiltable; converter installed in aluminium spotlight housing; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 3000 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 95; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; including high quality aluminium reflector with spherical reflector; high gloss anodised; neutral colour reflection through absolute freedom from interference colour; for brilliant object staging; precise radiation characteristic with 12° beam; installed and exchanged without tools; optical attachments available as accessories; degree of protection IP20; PC1 220-240V; adapter for toolless insertion or movement on a variety of 3-phase power tracks; adapter fixation by means of set screw; incl. DALI-2 converter; point outlet, either in surface mounted housing or recessed housing, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;


Light distribution



spot 12°

h (m)	E0° (lx)	ø (m)
1	17900	0.20
2	4500	0.40
3	2000	0.60
4	1100	0.81
5	700	1.01

Product drawing



<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)

<sup>3</sup> incl. optical losses and the efficiency of the operating device (converter)

<sup>4</sup> incl. optical losses

Installation instructions



Lighting calculator

