

VARO 80

track
080-6210617F



Project / Type _____

Notes _____

Count / Date _____



General

Ceiling , Track _____

tilt max 90° _____

rotation 355° _____

white , RAL 9016 ¹ _____

IP20 _____

2700 lm _____

LED

4000 K _____

CRI ≥ 90 _____

L90 / 50000 h _____

initial MacAdam ≤ 3 SDCM _____

R_g: 96 , R_f: 89 , R₍₁₋₁₅₎: 89 _____

MR 0.84 _____

MDER 0.76 _____

Optical

flood _____

beam angle 38° _____

Electrical

non DIM _____

220-240 V _____

system 28.8 W _____

system 94 lm/W² _____

PC1 _____

Physical


diameter 87 mm _____

height 145 mm _____

1 kg _____

Track light made of die-cast aluminium; surface white powder coated; 355° rotatable and 90° tiltable; converter integrated into spotlight head; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 4000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 90; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; including high quality aluminium reflector with spherical reflector; high gloss anodised; neutral colour reflection through absolute freedom from interference colour; for brilliant object staging; precise radiation characteristic with 38° beam; installed and exchanged without tools; optical attachment available as accessory; accessories are listed separately; degree of protection IP20; PC1; 220-240 V; incl. converter, non dimmable; adapter for toolless insertion or movement on a variety of 3-phase power tracks; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;


Light distribution



flood 38°

h (m)	E0° (lx)	ø (m)
1	6110	0.68
2	1530	1.37
3	680	2.05
4	380	2.73
5	240	3.42

Product drawing



¹ RAL code
² FIXTURE: incl. consideration of optical losses & internal control unit losses SYSTEM: incl. consideration of optical losses, internal control unit losses & operating device efficiency.

Installation instructions



Lighting calculator

