

HEX-O 500

suspended group
073-635153XP



Project / Type	
Notes	
Count / Date	



RG0 IEC 62471	220-240V	X-PERT	X-PERT
------------------	----------	--------	--------

General
Ceiling , Suspended
special colours
IP20
1870 lm

LED
3000 K
CRI ≥ 80
L90 / 50000 h
photobio. safety RG 0 - no Risk
initial MacAdam ≤ 3 SDCM
MR 0.54
MDER 0.49


Optical
Microprismatic
microprismatic
UGR < 19 , ≥65° <3000 cd/m²
PstLM ≤ 1.0 ¹
SVM ≤ 0.4 ¹

Electrical
DALI-2
system 16.3 W
PC1 220-240V
system 115 lm/W ²
1 DALI Addr.


Physical
cable 1500 mm (min. 500 mm)
length 500 mm
width 433 mm
height 100 mm
5.5 kg

Hexagonal light fitting from aluminium profile; seamlessly welded; surface special colours powder coated; pendant fitting with 1500mm cable suspension (1 cable); height adjustment without tools; canopy with 2 cable openings and plug-in terminal for through wiring, incl. feed available as an accessory; suitable for group installation; including rear rail for alignment of the housings; can be combined with all HEX-O ceiling and TRIG-O ceiling luminaires and acoustic elements; highly reflective coating for improved efficiency; microprismatic PMMA cover; completely homogeneous illumination; same luminance for all size versions; UGR ≤ 19; VDU compatible workplace luminaire according to DIN EN 12464-1; luminance above 65° ≤ 3000 cd/m²; light colour 3000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 80; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; degree of protection IP20; PC1 220-240V; photobiological safety according to IEC 62471 risk group RG 0 - no Risk; internal wiring in light halogen free; incl. DALI-2 converter; sound absorbing HEX-O ABSORBER available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



¹ Value of containing product at full load (undimmed)
² incl. optical losses and the efficiency of the operating device (converter)

Installation instructions	Lighting calculator

