

SONIC switch direct / indirect asymmetric power

free standing excentric pole
059-7942516P



Project / Type


Notes

Count / Date




Free standing luminaire with conical luminaire head in die-cast aluminium; round pedestal with recess for table stand; round aluminium upright tube aligned off-centre; surface dark grey powder coated; direct/indirect illumination characteristic; indirect component with special, inclined PCBs for asymmetric radiation characteristic; indirect component covered with clear acrylic glass; direct lighting portion: micro prismatic PMMA cover; perfectly unifrom illumination through use of a diffuse polycarbonate-based film; better light dispersion to transparency ratio; UGR ≤ 16 ; light colour 3000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 80 ; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; degree of protection IP20; PC1 220-240V; photobiological safety according to IEC 62471 risk group RG 0 - no Risk; incl. converter, non dimmable; incl. connection cable (3m) with safety plug; sound absorbing accessories available: acoustic elements made of high quality, self-supporting, recycled PET felt (high acoustic performance by doubling the material) or as an acoustically effective lampshade (large selection of colours) with sound absorbing properties; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



General

Floor , Standing

dark grey , RAL7021 ¹

IP20

indirect 9840 lm

direct 4260 lm

total 14100 lm

LED

3000 K

CRI ≥ 80

L90 / 50000 h

photobio. safety RG 0 - no Risk

initial MacAdam ≤ 3 SDCM

MR 0.54

MDER 0.49

Optical

Microprismatic

microprismatic

UGR < 16

PstLM ≤ 1.0 ²

SVM ≤ 0.4 ²

Electrical

non DIM switch

system 105 W

PC1 220-240V

system 134 lm/W ³

Physical

excentric pole 2050 mm

diameter 500 mm

height 2102 mm

17.9 kg

¹ RAL code ² Value of containing product at full load (undimmed)
³ incl. optical losses and the efficiency of the operating device (converter)

Installation instructions

