

TASK square direct / indirect power

free standing
059-293205XZ



Project / Type


Notes

Count / Date




Free standing luminaire with square head with rounded edges in aluminium; extremely flat design (only 15mm); round aluminium tube support; base stand with recess for table stand; modern shape in elegant design for discerning requirements; surface special colours powder coated; direct light distribution through LGP body (Light Guiding Prism); side coupled light directed downwards by laser engraving; indirect light component with special PCBs for increased luminous flux and maximum ceiling illumination; microprismatic PMMA cover; completely homogeneous illumination; UGR ≤ 10 ; VDU compatible workplace luminaire according to DIN EN 12464-1; luminance above $65^\circ \leq 1500 \text{ cd/m}^2$; light colour 3000 K; binning initial MacAdam $\leq 3 \text{ SDCM}$; CRI ≥ 90 ; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; degree of protection IP20; PC1; 220-240 V; including TOUCH DIM control for individual control of the brightness; incl. connection cable (3m) with safety plug; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



General

Floor , Standing

special colours

IP20

indirect 10000 lm

direct 2280 lm

total 12280 lm

LED

3000 K

CRI ≥ 90

L90 / 50000 h

initial MacAdam $\leq 3 \text{ SDCM}$

R_g: 96 , R_f: 90 , R₍₁₋₁₅₎: 90

MR 0.61

MDER 0.56

Optical

Microprismatic

microprismatic

UGR < 10 , $\geq 65^\circ < 1500 \text{ cd/m}^2$

P_{stLM} ≤ 1.0 ¹

SVM ≤ 0.4 ¹

Electrical

touch DIM on pole

220-240 V

system 92 W

system 133 lm/W²

PC1

Physical

H-shape

length 600 mm

width 600 mm

height 2000 mm

20.2 kg

¹ Value of containing product at full load (undimmed)
² FIXTURE: incl. consideration of optical losses & internal control unit losses SYSTEM: incl. consideration of optical losses, internal control unit losses & operating device efficiency.

Installation instructions

