

# TULA nano suspended

MOVE IT 25 / 25 S / 45

050-1711418M



Project / Type \_\_\_\_\_

Notes \_\_\_\_\_

Count / Date \_\_\_\_\_



## General

Ceiling , Track Suspended \_\_\_\_\_

black , RAL9005 <sup>1</sup> \_\_\_\_\_

IP20 \_\_\_\_\_

691 lm \_\_\_\_\_

## LED

2700 K \_\_\_\_\_

CRI ≥ 90 \_\_\_\_\_

initial MacAdam ≤ 2 SDCM \_\_\_\_\_

R<sub>g</sub>: 99 , R<sub>r</sub>: 91 , R<sub>f(1-15)</sub>: 89 \_\_\_\_\_

MR 0.53 \_\_\_\_\_

MDER 0.48 \_\_\_\_\_

## Optical

medium \_\_\_\_\_

beam angle 24° \_\_\_\_\_

PstLM ≤ 1.0 <sup>2</sup> \_\_\_\_\_

SVM ≤ 0.4 <sup>2</sup> \_\_\_\_\_

## Electrical

non DIM \_\_\_\_\_

system 12.1 W \_\_\_\_\_

PC3 \_\_\_\_\_

system 57 lm/W<sup>3</sup> \_\_\_\_\_

## Physical

diameter 26 mm \_\_\_\_\_


height 500 mm \_\_\_\_\_

0.35 kg \_\_\_\_\_

1500 mm \_\_\_\_\_

Decorative pendant light inset made of aluminium; surface black powder coated; light inset can be installed and moved without tools by means of magnetic holders+locking; power supplied via MOVE IT system track profile; hot plug protection; pendant fitting with 1500mm suspension, incl. feed (black), can be individually shortened; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; energy efficient LEDs with high CRI; good glare control through recessed light point level; incl. high quality lens system; precise radiation characteristic with 24° beam; degree of protection IP20; PC3; non-dimmable; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;


## Light distribution



medium 24°

h (m)	E0° (lx)	ø (m)
1	2820	0.43
2	700	0.85
3	310	1.28
4	180	1.71
5	110	2.13

## Product drawing



<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)  
<sup>3</sup> incl. optical losses and the efficiency of the operating device (converter)

## Installation instructions



## Lighting calculator

