

BETO sensor direct / indirect power

free standing T-shape
074-6955577B



Project / Type _____

Notes _____

Count / Date _____



General

Floor , Standing _____

white , RAL 9010 ¹ _____

Reflector dark chrome _____

IP20 _____

indirect 6630 lm _____

direct 1490 lm _____

total 8120 lm _____

LED

3000 K _____

CRI ≥ 80 _____

L90 / 50000 h _____

initial MacAdam ≤ 3 SDCM _____

MR 0.56 _____

MDER 0.51 _____

Optical

Reflector _____

asymmetric _____

UGR ≤ 10 _____

PstLM ≤ 1.0 ² _____

SVM ≤ 0.4 ² _____

Electrical

ESSENTIAL sensor (brightness & presence) _____

220-240 V _____

system 66 W _____

system 123 lm/W³ _____

PC1 _____

Physical

T-shape _____

length 1055 mm _____

width 42 mm _____


height 2100 mm _____

¹ RAL code ² Value of containing product at full load (undimmed)
³ incl. consideration of optical losses, internal control unit losses
& operating device efficiency


Installation instructions



Light distribution



Product drawing



BETO sensor direct / indirect power

free standing T-shape
074-6955577B



Project / Type

Notes

Count / Date

Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.98	0.96	0.94	0.92	0.9
LSF	1	1	1	1	1

MF

MF

LMF^a

LMF × RSMF × LLMF × LSF

Maintenance Factor

Luminaire Maintenance Factor

RSMF^a

LLMF

LSF

Room Surface Maintenance Factor

Lamp Lumens Maintenance Factor

Lamp Survival Faktor

^a According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

Circuit Breaker Types

Automatic Circuit Breaker Type	Number of Fixtures
B10	13
B13	17
B16	21
B20	27
C10	21
C13	28
C16	35
C20	45

