

SASSO 60 round adjustable  
ceiling  
048-31104379W



Project / Type \_\_\_\_\_

Notes \_\_\_\_\_

Count / Date \_\_\_\_\_



**General**

Ceiling , Surface \_\_\_\_\_

tilt max 30° \_\_\_\_\_

rotation 360° \_\_\_\_\_

white , RAL9016/gold <sup>1</sup> \_\_\_\_\_

Inner colour gold \_\_\_\_\_

IP20 \_\_\_\_\_

822 lm \_\_\_\_\_

**LED**

2700 K \_\_\_\_\_

CRI ≥ 90 \_\_\_\_\_

L80 / 50000 h \_\_\_\_\_

initial MacAdam ≤ 2 SDCM \_\_\_\_\_

R<sub>g</sub>: 99 , R<sub>r</sub>: 91 , R<sub>t(1-15)</sub>: 89 \_\_\_\_\_

MR 0.53 \_\_\_\_\_

MDER 0.48 \_\_\_\_\_

**Optical**


wide flood \_\_\_\_\_

beam angle 54° \_\_\_\_\_


≥65° <3000 cd/m<sup>2</sup> \_\_\_\_\_

Cylindrical surface mounted spotlight in die-cast aluminium; suitable for ceiling mounting; surface white powder coated; Inner colour lacquered in gold; 360° rotatable and 30° tiltable; luminaire housing can be attached to mounting plate without tools by interlock; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 54° beam; degree of protection IP20; PC1; incl. DALI-2 converter; flicker-free visual comfort through analogue current control (minimum value 1%); converter integrated into spotlight head; luminaire for through wiring; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



**Electrical**

DALI-2 \_\_\_\_\_

220-240 V \_\_\_\_\_

system 10.4 W \_\_\_\_\_

PC1 \_\_\_\_\_

system 79 lm/W<sup>2</sup> \_\_\_\_\_

1 DALI Addr. \_\_\_\_\_

**Physical**

diameter 72 mm \_\_\_\_\_

height 108 mm \_\_\_\_\_

0.5 kg \_\_\_\_\_

<sup>1</sup> RAL code  
<sup>2</sup> incl. optical losses and the efficiency of the operating device (converter)

Installation instructions



Lighting calculator

