

SETA 60 CONEX reflector

direct socket / socket

surface / suspended system
058-4034637R



Project / Type


Notes

Count / Date



Luminaire housing made of extruded aluminium profile; extremely slim design (only Ø 60 mm) linear; converter integrated into luminaire housing; for lighting systems; surface white powder coated; for ceiling surface mounting or suspended mounting (1500 mm cable suspension - oblique or straight - as an accessory); easy installation using ceiling clips (available as an accessory) or with integrated toolless suspension height adjustment on the luminaire; canopy for through wiring (available as an accessory); electrical connection of the luminaires via plug/socket system; connectors (L-, T- or X-shape) available as an accessory; luminaire connection rotatable around its own axis, which means that any spatial angle can be realized; extruded profile for improved thermal management; high gloss reflector with faceted design; $UGR \leq 19$; VDU compatible workplace luminaire according to DIN EN 12464-1; luminance above $65^\circ \leq 1500 \text{ cd/m}^2$; light colour 4000 K; binning initial MacAdam $\leq 3 \text{ SDCM}$; $CRI \geq 80$; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; degree of protection IP20; PC1 220-240V; incl. DALI-2 converter; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



General

Ceiling , Suspended

white , RAL9010 ¹

chrome

IP20

3010 lm

LED

4000 K

$CRI \geq 80$

L90 / 50000 h

initial MacAdam $\leq 3 \text{ SDCM}$

MR 0.72

MDER 0.65

Optical

Reflector

symmetric

$UGR < 19, \geq 65^\circ < 1500 \text{ cd/m}^2$

$PstLM \leq 1.0$ ²

$SVM \leq 0.4$ ²

Electrical

DALI-2

system 18.6 W

PC1 220-240V

system 162 lm/W³

1 DALI Addr.

Physical

length 1181 mm

width 60 mm

height 60 mm

¹ RAL code ² Value of containing product at full load (undimmed)
³ incl. optical losses and the efficiency of the operating device (converter)

Installation instructions



Lighting calculator

