

# MINO 60 mid lumen

surface

046-41L3017G



Project / Type

Notes

Count / Date



220-240V

X-PERT

UGR

≤ 19

cd/m<sup>2</sup>

≤ 3000

CRI

≥ 90

X-PERT

General

Ceiling , Surface

white , RAL9010 <sup>1</sup>

1060 lm/m

IP20

925 lm

LED

3000 K

CRI ≥ 90

L90 / 50000 h

photobio. safety RG 0 - no Risk

initial MacAdam ≤ 3 SDCM

R<sub>g</sub>: 99 , R<sub>f</sub>: 91 , R<sub>(1-15)</sub>: 89

MR 0.61

MDER 0.55

Optical

Microprismatic

microprismatic

UGR < 19 , ≥65° <3000 cd/m<sup>2</sup>

PstLM ≤ 1.0 <sup>2</sup>

SVM ≤ 0.4 <sup>2</sup>

Electrical

non DIM

10.3 W

PC1 220-240V

90 lm/W

12 W/m

Physical

length 880 mm

width 60 mm

height 80 mm

2.59 kg

<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)

Light distribution



Product drawing



Installation instructions



Lighting calculator



# MINO 60 mid lumen

surface

046-41L3017G



Project / Type

Notes

Count / Date

## Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.98	0.96	0.94	0.92	0.9
LSF	1	1	1	1	1

MF

LMF × RSMF × LLMF × LSF

MF

Maintenance Factor

LMF<sup>a</sup>

Luminaire Maintenance Factor

RSMF<sup>a</sup>

Room Surface Maintenance Factor

LLMF

Lamp Lumens Maintenance Factor

LSF

Lamp Survival Faktor

<sup>a</sup> According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

## Circuit Breaker Types

Automatic Circuit Breaker Type	Number of Fixtures
B10	9
B13	13
B16	15
B20	18
C10	18
C13	26
C16	30
C20	36

