

MINO 40 flex mid lumen

ceiling / suspended system

042-011F037 042-100201W 006-4210010H



Project / Type

Notes

Count / Date



General

Ceiling , Suspended

RAL Traffic white , RAL 9016 ¹

pure white

1360 lm/m

IP20

1360 lm

LED

3000 K

CRI \geq 90

L90 / 50000 h

photobio. safety RG 0 - no Risk

initial MacAdam \leq 3 SDCM

R_g: 99 , R_r: 91 , R₍₁₋₁₅₎: 89

MR 0.61

MDER 0.55

Optical

High Performance Opal

opal (lambertsch)

P_{stLM} \leq 1.0 ²

SVM \leq 0.4 ²

Electrical

DALI-2

system 12.1 W

PC1 220-240V

system 112 lm/W³

12 W/m

Physical

length 1000 mm

width 40 mm


height 65 mm

5.5 kg

L (mm): 500 - 1000, breakable every 62.5mm

Luminaire housing made of extruded aluminium profile; angular design; for continuous lighting systems; light tight final end caps made of aluminium (available as an accessory); no visible screws; surface traffic white powder coated; same RAL colour as spotlight modules; for ceiling surface mounting or suspended mounting (1500 mm cable suspension as an accessory); height adjustment without tools; luminaire profile can be pre-mounted; pre-assembled power rail for power supply in luminaire profile; voltage tap of the light inset on the power rail; remaining lamp components mounted without tools; LED light inset consisting of highly reflective lacquered aluminium for improved thermal management; light colour 3000 K; binning initial MacAdam \leq 3 SDCM; CRI \geq 90; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; HPO (High Performance Opal) cover for uniform illumination; degree of protection IP20; PC1 220-240V; photobiological safety according to IEC 62471 risk group RG 0 - no Risk; internal wiring in light halogen free; incl. DALI-2 converter; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



¹ RAL code ² Value of containing product at full load (undimmed)

³ incl. optical losses and the efficiency of the operating device (converter)

Installation instructions



Lighting calculator

