

# VARO 80 S

track

180-6424238M



Project / Type

Notes

Count / Date



## General

Ceiling , Track

tilt max 90°

rotation 355°

black , RAL 9005 <sup>1</sup>

IP20

1940 lm

## LED

3500 K

CRI ≥ 90

L80 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 99 , R<sub>f</sub>: 92 , R<sub>(1-15)</sub>: 93

MR 0.61

MDER 0.55

## Optical

medium

beam angle 27°

PstLM ≤ 1.0 <sup>2</sup>

SVM ≤ 0.4 <sup>2</sup>

Track light made of die-cast aluminium; surface black powder coated; 355° rotatable and 90° tiltable; integrated converter in the plastic adapter; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 3500 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; including high quality aluminium reflector with spherical reflector; high gloss anodised; neutral colour reflection through absolute freedom from interference colour; for brilliant object staging; precise radiation characteristic with 27° beam; installed and exchanged without tools; optical attachments available as accessories; optical attachments can be combined; accessories are listed separately; degree of protection IP20; PC2; 220-240 V; incl. DALI-2 converter; adapter for toolless insertion or movement on a variety of 3-phase power tracks; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

## Electrical

DALI-2

220-240 V

system 13.0 W

system 149 lm/W<sup>3</sup>

PC2

1 DALI Addr.


## Physical

diameter 87 mm

height 80 mm

0.5 kg


## Light distribution



medium 27°

h (m)	EO° (lx)	ø (m)
1	6220	0.49
2	1550	0.97
3	690	1.46
4	390	1.95
5	250	2.43

## Product drawing



<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)  
<sup>3</sup> incl. consideration of optical losses, internal control unit losses & operating device efficiency

## Installation instructions



## Lighting calculator

