

MOVE IN 45 square

trim

063-8421416S 063-8842117 002-90720



Project / Type

Notes

Count / Date



General

Ceiling , Semi-Recessed

brushed aluminium

Mounting set traffic white

IP20

1030 lm

LED

2700 K

CRI \geq 90

L80 / 50000 h

initial MacAdam \leq 2 SDCM

R_g: 99 , R_r: 91 , R_{t(1-5)}: 89

MR 0.53

MDER 0.48

Optical

spot

beam angle 12°

PstLM \leq 1.0 ¹

SVM \leq 0.4 ¹

Electrical

DALI-2

system 14.9 W

inset 12.7 W

37 Vf

350 mA

PC2 220-240V


system 69 lm/W²

inset 81 lm/W³

1 DALI Addr.

Square spotlight element in aluminium; surface brushed aluminium; installation without tools in mounting set due to patented ball catch system; recessed light with trim traffic white; suitable for ceiling thickness of 2-25 mm; spotlight element height adjustable without tools: flush with the ceiling, or extended 25 mm or 35 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam \leq 2 SDCM; CRI \geq 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; high quality, aluminium, vapour deposition coated reflector with faceted lens design; precise radiation characteristic with 12° beam; good glare control through recessed light point level; optical attachment available as accessory; accessories are listed separately; degree of protection IP20; PC2 220-240V; incl. DALI-2 converter; converter wired secondary side; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



spot 12°

h (m)	E0° (lx)	ø (m)
1	13000	0.21
2	3300	0.42
3	1400	0.63
4	800	0.84
5	500	1.06

Product drawing



Physical

trim

diameter 78 mm

height 105 mm

0.24 kg

Cutout

diameter 70 mm

min. ceiling thickness 2 mm

max. ceiling thickness 25 mm

recessed depth 175 mm

¹ Value of containing product at full load (undimmed)

² incl. optical losses and the efficiency of the operating device (converter)

³ incl. optical losses

Installation instructions



Lighting calculator

