

# MINO 60 direct / indirect high lumen ceiling /

suspended system  
046-502551XZ



Project / Type \_\_\_\_\_

Notes \_\_\_\_\_

Count / Date \_\_\_\_\_



RG0  
IEC 62471

220-240V

X-PERT

X-PERT

### General

Ceiling , Suspended

special colours

3500 lm/m

IP20

indirect 2110 lm

direct 3000 lm

total 5110 lm

### LED

3000 K

CRI ≥ 80

L90 / 50000 h

photobio. safety RG 0 - no Risk

initial MacAdam ≤ 3 SDCM

MR 0.56

MDER 0.51

### Optical

Microprismatic

microprismatic

UGR < 19

### Electrical

non DIM

system 43 W

PC1 220-240V

system 119 lm/W<sup>1</sup>

29 W/m

### Physical

length 1464 mm


width 60 mm

height 80 mm

3.8 kg

Luminaire housing made of extruded aluminium profile; angular design; for continuous lighting systems; light tight final end caps made of aluminium (available as an accessory); no visible screws; surface special colours powder coated; for suspended mounting (1500 mm cable suspension as an accessory); with integrated toolless suspension height adjustment on the luminaire; spring clip attachment to the luminaire; freely positionable; LED light inset consisting of highly reflective lacquered aluminium for improved thermal management; light colour 3000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 80; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; micro prismatic PMMA diffuser incl. diffuser film for homogeneous illumination and reduced luminance; UGR ≤ 19; direct/indirect illumination characteristic; indirect light component with integrated PC boards for maximum, homogeneous ceiling illumination; degree of protection IP20; PC1 220-240V; photobiological safety according to IEC 62471 risk group RG 0 - no Risk; internal wiring in light halogen free; incl. converter, non dimmable; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

### Light distribution



### Product drawing



<sup>1</sup> incl. optical losses and the efficiency of the operating device (converter)

### Installation instructions



### Lighting calculator

