

MINO 60 direct / indirect mid lumen ceiling /

suspended system
046-501551GH



Project / Type _____

Notes _____

Count / Date _____



RG0
IEC 62471

220-240V

X-PERT

X-PERT

General

Ceiling , Suspended _____

grey , RAL9006 ¹ _____

2680 lm/m _____

IP20 _____

indirect 1450 lm _____

direct 2470 lm _____

total 3920 lm _____

LED

3000 K _____

CRI ≥ 80 _____

L90 / 50000 h _____

photobio. safety RG 0 - no Risk _____

initial MacAdam ≤ 3 SDCM _____

MR 0.56 _____

MDER 0.51 _____

Optical

High Performance Opal _____

opal (lamberts) _____

Electrical

non DIM _____

system 29.1 W _____

PC1 220-240V _____

system 135 lm/W² _____

20 W/m _____

Physical

length 1464 mm _____


width 60 mm _____

height 80 mm _____

3.8 kg _____

Luminaire housing made of extruded aluminium profile; angular design; for continuous lighting systems; light tight final end caps made of aluminium (available as an accessory); no visible screws; surface grey powder coated; for suspended mounting (1500 mm cable suspension as an accessory); with integrated toolless suspension height adjustment on the luminaire; spring clip attachment to the luminaire; freely positionable; LED light inset consisting of highly reflective lacquered aluminium for improved thermal management; light colour 3000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 80; min. 90% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; HPO (High Performance Opal) cover for uniform illumination; direct/indirect illumination characteristic; indirect light component with integrated PC boards for maximum, homogeneous ceiling illumination; degree of protection IP20; PC1 220-240V; photobiological safety according to IEC 62471 risk group RG 0 - no Risk; internal wiring in light halogen free; incl. converter, non dimmable; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



¹ RAL code
² incl. optical losses and the efficiency of the operating device (converter)

Installation instructions



Lighting calculator

