

# NOBA 60 suspended 1 lamp

MOVE IT PRO  
086-71000347W



Project / Type

Notes

Count / Date



General

Ceiling , Track Suspended

chrome

Converter Traffic White

IP20

1010 lm

LED

3000 K

CRI ≥ 90

L80 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 100 , R<sub>f</sub>: 91 , R<sub>f(1-15)</sub>: 88

MR 0.59

MDER 0.53

Optical

wide flood

beam angle 67°

PstLM ≤ 1.0 <sup>1</sup>

SVM ≤ 0.4 <sup>1</sup>

Electrical

DALI-2

220-240 V

system 10.0 W

system 101 lm/W<sup>2</sup>

PC2

1 DALI Addr.

Physical

length 60 mm

width 60 mm


height 60 mm

adapter 402 mm

suspension 2000 mm

<sup>1</sup> Value of containing product at full load (undimmed)  
<sup>2</sup> FIXTURE: incl. consideration of optical losses & internal control unit losses SYSTEM: incl. consideration of optical losses, internal control unit losses & operating device efficiency.

## Light distribution



wide flood 67°

h (m)	E0° (lx)	ø (m)
1	960	1.31
2	240	2.63
3	107	3.94
4	60	5.26
5	38	6.57

## Product drawing



Installation instructions

Lighting calculator



# NOBA 60 suspended 1 lamp

MOVE IT PRO  
086-71000347W



Project / Type

Notes

Count / Date

### Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.96	0.92	0.88	0.85	0.81
LSF	1	1	1	1	1
MF	LMF × RSMF × LLMF × LSF		RSMF <sup>a</sup>	Room Surface Maintenance Factor	
MF	Maintenance Factor		LLMF	Lamp Lumens Maintenance Factor	
LMF <sup>a</sup>	Luminaire Maintenance Factor		LSF	Lamp Survival Faktor	

<sup>a</sup> According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

### Circuit Breaker Types

Automatic Circuit Breaker Type	Number of Fixtures
B10	27
B13	34
B16	43
C10	33
C13	42
C16	53

### Mounting accessories

#### HOOK

COLOUR	Ø (MM)	ARTICLE NUMBER(S)
traffic white	16	030-1000017
jet black	16	030-1000018

