

# NOBA 60 suspended 2 lamps

MOVE IT PRO

086-71100347W



Project / Type

Notes

Count / Date



## General

Ceiling , Track Suspended

chrome

Converter Traffic White

IP20

1970 lm

## LED

3000 K

CRI  $\geq 90$

L80 / 50000 h

initial MacAdam  $\leq 2$  SDCM

R<sub>g</sub>: 100 , R<sub>f</sub>: 91 , R<sub>f(1-15)</sub>: 88

MR 0.59

MDER 0.53

## Optical

wide flood

beam angle 67°

PstLM  $\leq 1.0$ <sup>1</sup>

SVM  $\leq 0.4$ <sup>1</sup>

## Electrical

DALI-2

19.2 W

PC2 220-240V

103 lm/W

1 DALI Addr.

## Physical

length 60 mm

width 60 mm


height 60 mm

402 (adapter) mm

suspension 2000 mm

<sup>1</sup> Value of containing product at full load (undimmed)


## Light distribution



wide flood 67°

h (m)	E0° (lx)	ø (m)
1	937	1.31
2	234	2.63
3	104	3.94
4	59	5.26
5	37	6.57

## Product drawing



## Lighting calculator



# NOBA 60 suspended 2 lamps

MOVE IT PRO  
086-71100347W



Project / Type

Notes

Count / Date

### Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.96	0.92	0.88	0.85	0.81
LSF	1	1	1	1	1
MF	LMF × RSMF × LLMF × LSF		RSMF <sup>a</sup>	Room Surface Maintenance Factor	
MF	Maintenance Factor		LLMF	Lamp Lumens Maintenance Factor	
LMF <sup>a</sup>	Luminaire Maintenance Factor		LSF	Lamp Survival Faktor	

<sup>a</sup> According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.

### Circuit Breaker Types

Automatic Circuit Breaker Type	Number of Fixtures
B10	27
B13	34
B16	43
C10	33
C13	42
C16	53

### Mounting accessories

#### HOOK

COLOUR	Ø (MM)	ARTICLE NUMBER(S)
traffic white	16	030-1000017
jet black	16	030-1000018

