



Project / Type _____


Notes _____

Count / Date _____




Miniature rectangular lamp made of aluminium; angular design; surface lacquered in black; plug and play electrical connector system for toolless mounting; different mechanical and electrical poles available - for flexible system design (available as an accessory); equipped with miniature spotlight heads; light colour 4000 K; binning initial MacAdam ≤ 3 SDCM; CRI ≥ 95 ; min. 85% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 39° beam; light inset rotatable; degree of protection IP20; PC3 24V; photobiological safety according to IEC 62471 risk group RG 1 - low Risk; accessories are listed separately; light source replaceable by an authorized professional;

Light distribution



flood 39°		
h (m)	EO° (lx)	ø (m)
1	733	0.71
2	183	1.42
3	81	2.13
4	46	2.84
5	29	3.55

Product drawing



General

Showcase , Standing _____

rotation 360° _____

black , RAL9021 ¹ _____

IP20 _____

Interior _____

360 lm _____

LED

4000 K _____

CRI ≥ 95 _____

L85 / 50000 h _____

photobio. safety RG 1 - low Risk _____

initial MacAdam ≤ 3 SDCM _____

R_g: 100 , R_f: 94 , R₍₁₋₁₅₎: 96 _____

MR 0.87 _____

MDER 0.78 _____

Optical

flood _____

beam angle 39° _____

Electrical

excl. driver _____

24 V _____

system 4.5 W _____

PC3 24V _____

inset 108 lm/W² _____

Physical

length 400 mm _____

width 11 mm _____

height 29 mm _____

¹ RAL code ² incl. optical losses

Installation instructions





Project / Type

Notes

Count / Date

Maintenance Factors

Operating Time [h]	10 000	20 000	30 000	40 000	50 000
LLMF	0.983	0.957	0.931	0.906	0.881
LSF	1	1	1	1	1

MF

MF

LMF^a

LMF × RSMF × LLMF × LSF

Maintenance Factor

Luminaire Maintenance Factor

RSMF^a

LLMF

LSF

Room Surface Maintenance Factor

Lamp Lumens Maintenance Factor

Lamp Survival Faktor

^a According to "CIE 97, Maintenance of indoor electric lighting systems", 2005, ISBN 3-900-734-34-8. The values must be determined by the planner.