

# SASSO 100 round adjustable trimless soft acoustic ceiling

048-2720911W 048-2796117 002-90780



Project / Type \_\_\_\_\_


Notes \_\_\_\_\_

Count / Date \_\_\_\_\_



Round recessed spotlight in die-cast aluminium; 1 lamp; surface black; 360° rotatable and 30° tiltable; installation without tools in mounting set due to patented ball catch system; round installation housing; traffic white; for trimless installation in soft acoustic ceilings; suitable for ceiling thickness of 25-40 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam  $\leq 2$  SDCM; CRI  $\geq 90$ ; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 60° beam; degree of protection from below IP40 (from above IP20); PC2 220-240V; incl. converter, non dimmable; through wiring connection box, 3-pole or 5-pole, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

## Light distribution



## Product drawing



## General

Ceiling , Recessed  
tilt max 30°  
rotation 360°  
black , RAL9005 <sup>1</sup>  
Traffic black  
front IP40 , back IP20  
2200 lm

## LED

2700 K  
CRI  $\geq 90$   
L80 / 50000 h  
initial MacAdam  $\leq 2$  SDCM  
R<sub>g</sub>: 97 , R<sub>r</sub>: 91 , R<sub>(1-15)</sub>: 87  
MR 0.52  
MDER 0.47

## Optical

wide flood  
beam angle 60°  
 $\geq 65^\circ < 3000 \text{ cd/m}^2$

## Electrical

non DIM  
system 26.7 W  
inset 22.7 W  
36 Vf  
650 mA  
PC2 220-240V  
system 82 lm/W<sup>2</sup>  
inset 97 lm/W<sup>3</sup>

## Physical

trimless for acoustic ceiling  
diameter 114 mm  
height 95 mm  
0.47 kg

## Cutout

diameter 106 mm  
min. ceiling thickness 25 mm  
max. ceiling thickness 40 mm  
recessed depth 100 mm

<sup>1</sup> RAL code  
<sup>2</sup> incl. optical losses and the efficiency of the operating device (converter)  
<sup>3</sup> incl. optical losses

## Installation instructions



## Lighting calculator

