

# SASSO 100 round downlight trimless soft acoustic ceiling

048-2700911W 048-2796198 002-90780



Project / Type	
Notes	
Count / Date	



220-240V	IP20 IP44	X-PERT	X-PERT
----------	--------------	--------	--------

## General

Ceiling , Recessed
black , RAL9005 <sup>1</sup>
Traffic black
front IP44 , back IP20
2190 lm

## LED

2700 K
CRI ≥ 90
L80 / 50000 h
initial MacAdam ≤ 2 SDCM
R <sub>g</sub> : 97 , R <sub>f</sub> : 91 , R <sub>f(1-15)</sub> : 87
MR 0.52
MDER 0.47

## Optical

wide flood
beam angle 65°
≥65° <1500 cd/m <sup>2</sup>

## Electrical

non DIM
system 26.7 W
inset 22.7 W
36 Vf
650 mA
PC2 220-240V
system 82 lm/W <sup>2</sup>
inset 96 lm/W <sup>3</sup>

## Physical


trimless for acoustic ceiling
diameter 114 mm
height 75 mm
0.47 kg

## Cutout


diameter 100 mm
min. ceiling thickness 25 mm
max. ceiling thickness 40 mm
recessed depth 80 mm

Round recessed spotlight in die-cast aluminium; 1 lamp; surface black; installation without tools in mounting set due to patented ball catch system; round installation housing; Traffic black; for trimless installation in soft acoustic ceilings; suitable for ceiling thickness of 25-40 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 65° beam; degree of protection from below IP44 (from above IP20); PC2 220-240V; incl. converter, non dimmable; through wiring connection box, 3-pole or 5-pole, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

## Light distribution



## Product drawing



<sup>1</sup> RAL code  
<sup>2</sup> incl. optical losses and the efficiency of the operating device (converter)  
<sup>3</sup> incl. optical losses

## Installation instructions



## Lighting calculator

