

# SASSO 60 round downlight

## trim soft acoustic ceiling

048-2602911W 048-2696397 002-90742



Project / Type

Notes

Count / Date



360° rotation

220-240V

IP20 / IP44

X-PERT

X-PERT

### General

Ceiling , Recessed

rotation 360°

black , RAL9005 <sup>1</sup>

Signal white

front IP44 , back IP20

848 lm

### LED

2700 K

CRI ≥ 90

L80 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 97 , R<sub>f</sub>: 91 , R<sub>{1-15}</sub>: 87

MR 0.52

MDER 0.47

### Optical

wide flood

beam angle 55°

≥65° <1500 cd/m<sup>2</sup>

PstLM ≤ 1.0 <sup>2</sup>

SVM ≤ 0.4 <sup>2</sup>

### Electrical

non DIM

system 10.2 W

inset 8.7 W

36 Vf

250 mA

PC2 220-240V

system 83 lm/W<sup>3</sup>

inset 98 lm/W<sup>4</sup>

### Physical

with trim for acoustic ceiling

diameter 80 mm

height 48 mm

0.2 kg

### Cutout

diameter 74 mm


min. ceiling thickness 25 mm

max. ceiling thickness 40 mm


recessed depth 60 mm

Round recessed spotlight in die-cast aluminium; 1 lamp; surface black; installation without tools in mounting set due to patented ball catch system; round installation housing; with trim Signal white; for installation in soft acoustic ceilings; suitable for ceiling thickness of 25-40 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 55° beam; degree of protection from below IP44 (from above IP20); PC2 220-240V; incl. converter, non dimmable; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

### Light distribution



### Product drawing



<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)

<sup>3</sup> incl. optical losses and the efficiency of the operating device (converter)

<sup>4</sup> incl. optical losses

### Installation instructions



### Lighting calculator

