

SASSO 60 round downlight trimless soft acoustic ceiling

048-2602117W 048-2696198 002-90742



Project / Type _____


Notes _____

Count / Date _____




Round recessed spotlight in die-cast aluminium; 1 lamp; surface white; installation without tools in mounting set due to patented ball catch system; round installation housing; Traffic black; for trimless installation in soft acoustic ceilings; suitable for ceiling thickness of 25-40 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 4000 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90 ; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 55° beam; degree of protection from below IP44 (from above IP20); PC2 220-240V; incl. converter, non dimmable; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

Light distribution



Product drawing



General

Ceiling , Recessed _____

rotation 360° _____

white , RAL9016 ¹ _____

Traffic black _____

front IP44 , back IP20 _____

988 lm _____

LED

4000 K _____

CRI ≥ 90 _____

L80 / 50000 h _____

initial MacAdam ≤ 2 SDCM _____

R_g: 98 , R_f: 90 , R₍₁₋₁₅₎: 88 _____

MR 0.8 _____

MDER 0.72 _____

Optical

wide flood _____

beam angle 55° _____

$\geq 65^\circ < 1500 \text{ cd/m}^2$ _____

PstLM ≤ 1.0 ² _____

SVM ≤ 0.4 ² _____

Electrical

non DIM _____

system 10.0 W _____

inset 8.5 W _____

36 Vf _____

250 mA _____

PC2 220-240V _____

system 99 lm/W³ _____

inset 116 lm/W⁴ _____

Physical

trimless for acoustic ceiling _____

diameter 80 mm _____

height 48 mm _____

0.22 kg _____

Cutout

diameter 74 mm _____

min. ceiling thickness 25 mm _____

max. ceiling thickness 40 mm _____

recessed depth 90 mm _____

¹ RAL code ² Value of containing product at full load (undimmed)
³ incl. optical losses and the efficiency of the operating device (converter)
⁴ incl. optical losses

Installation instructions



Lighting calculator

