

# SASSO 100 round adjustable

semi-recessed

048-34019177W 002-90767



Project / Type \_\_\_\_\_

Notes \_\_\_\_\_

Count / Date \_\_\_\_\_



## General

Ceiling , Semi-Recessed  
 tilt max 20°  
 rotation 360°  
 white , RAL9016/white <sup>1</sup>  
 Inner colour white  
 IP20  
 1670 lm

## LED

2700 K  
 CRI ≥ 90  
 L80 / 50000 h  
 initial MacAdam ≤ 2 SDCM  
 R<sub>g</sub>: 97 , R<sub>r</sub>: 91 , R<sub>(1-15)</sub>: 87  
 MR 0.52  
 MDER 0.47

## Optical

wide flood  
 beam angle 59°  
 P<sub>stLM</sub> ≤ 1.0 <sup>2</sup>  
 SVM ≤ 0.4 <sup>2</sup>

## Electrical

DALI-2  
 system 17.9 W  
 inset 15.2 W  
 36 Vf  
 450 mA  
 PC2 220-240V  
 system 93 lm/W<sup>3</sup>  
 inset 110 lm/W<sup>4</sup>  
 1 DALI Addr.

## Physical


diameter 100 mm  
 height 115 mm  
 0.78 kg

## Cutout


recessed depth 100 mm

Cylindrical semi-recessed spotlight made of aluminium; surface white (housing/light inset); 360° rotatable and 20° tiltable; luminaire housing can be attached to mounting plate without tools by interlock; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 2700 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 59° beam; degree of protection IP20; PC2 220-240V; incl. DALI-2 converter; flicker-free visual comfort through analogue current control (minimum value 1%); external converter for ceiling insertion; through wiring connection box, 3-pole or 5-pole, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

## Light distribution



## Product drawing



<sup>1</sup> RAL code <sup>2</sup> Value of containing product at full load (undimmed)  
<sup>3</sup> incl. optical losses and the efficiency of the operating device (converter)  
<sup>4</sup> incl. optical losses

## Installation instructions



## Lighting calculator

