

# SASSO 100 square downlight

trim

048-2710114W 048-279731G 002-90767



Project / Type

Notes

Count / Date



220-240V

IP20  
IP44

X-PERT

X-PERT

### General

Ceiling , Recessed

matt silver

Mounting set white aluminium

front IP44 , back IP20

1850 lm

### LED

4000 K

CRI ≥ 90

L80 / 50000 h

initial MacAdam ≤ 2 SDCM

R<sub>g</sub>: 98 , R<sub>r</sub>: 90 , R<sub>t(1-15)</sub>: 88

MR 0.8

MDER 0.72

### Optical

wide flood

beam angle 65°

≥65° <1500 cd/m<sup>2</sup>

PstLM ≤ 1.0 <sup>1</sup>

SVM ≤ 0.4 <sup>1</sup>

### Electrical

DALI-2

system 17.9 W

inset 15.2 W

36 V<sub>f</sub>

450 mA

PC2 220-240V

system 103 lm/W<sup>2</sup>

inset 121 lm/W<sup>3</sup>

1 DALI Addr.

### Physical

trim

length 118 mm

width 118 mm

height 75 mm

0.54 kg

### Cutout

length 112 mm

width 112 mm


min. ceiling thickness 2 mm

max. ceiling thickness 25 mm

recessed depth 80 mm

Recessed square spotlight in die-cast aluminium; 1 lamp; surface matt silver; installation without tools in mounting set due to patented ball catch system; square installation housing; with trim white aluminium; suitable for ceiling thickness of 2-25 mm; passive cooling of the LEDs through improved heat sink geometry; with COB (Chip on Board) technology for maximum efficiency; no appearance of multiple shadows; light colour 4000 K; binning initial MacAdam ≤ 2 SDCM; CRI ≥ 90; min. 80% of luminous flux after 50000 operating hours; energy efficient LEDs with high CRI; incl. high quality lens system; precise radiation characteristic with 65° beam; degree of protection from below IP44 (from above IP20); PC2 220-240V; incl. DALI-2 converter; through wiring connection box, 3-pole or 5-pole, available as an accessory; accessories are listed separately; light source replaceable by an authorized professional; control gear replaceable by an authorized professional;

### Light distribution



### Product drawing



# SASSO 100 square downlight

trim

048-2710114W 048-279731G 002-90767



Project / Type

Notes

Count / Date

Installation  
instructions



Lighting  
calculator

