



## SASSO 60 round

recessed

**EN** Round recessed spotlight; installation without tools in mounting set (trimless or with trim) with ball catch system; surface lacquered; installation possible in different housings; choice of adjustable / fixed symmetric or asymmetric radiation characteristic; variants with symmetric radiation characteristic: precise radiation characteristic due to high quality lens system; variants with asymmetric radiation characteristic: high-quality reflector with micro-faceted, aluminum-vaporised surface; COB (Chip on Board) technology for maximum efficiency (ADJUSTABLE and DOWNLIGHT); no multiple shadows; efficient LEDs with very good colour rendering

**FR** Spot rond encastrable ; montage sans outil en kit de montage (sans bord ou avec bord continu) par système à dé clic à bille ; surface laquée ; encastrement possible dans différents boîtiers ; au choix de l'orientation / symétrique Fixe ou asymétrique caractéristique du flux ; variantes à rayonnement sym. : caractéristiques de rayonn. précises grâce à l'optique à lentille ; variantes à rayonnement asymétrique : réflecteur de grande qualité avec surface à microfacettes, métallisée à l'aluminium ; Technologie COB (Chip on Board) pour efficacité maximale (ADJUSTABLE et DOWNLIGHT) ; pas d'ombres multiples ; LED économes en énergie à restitution de couleur élevée

### Quickinfo

2700 K, 3000 K, 3500 K, 4000 K,  
CWD 1800–3000 K  
CRI ≥ 90, 2 SDCM  
up to 118 lm/W  
L80 @ 50000h  
non DIM, DALI-2  
↓ IP44/↑ IP20

### Types



### Housing colours



### Inset colours



### Light distributions



rotatable 360°,  
tiltable 30°



wallwasher and  
ww floor inset



glare control  
(UGR ≤ 16)



60 mm  
recess depth



CWD  
1800–3000 K

### Order options

#### COLOUR TEMPERATURE ADJUSTABLE & DOWNLIGHT

|                 |   |
|-----------------|---|
| 2700K           | 9 |
| 3000K           | 0 |
| 3500K           | 2 |
| 4000K           | 1 |
| CWD 1800-3000K* |   |

\*only for DALI-2; not for DIN-RAIL LED Driver

#### COLOUR TEMPERATURE WALLWASHER & WW FLOOR

|                 |   |
|-----------------|---|
| 2700K           | 4 |
| 3000K           | 5 |
| 4000K           | 6 |
| CWD 1800-3000K* |   |

\*only for DALI-2; not for DIN-RAIL LED Driver

#### INSET COLOUR

|   |   |
|---|---|
| <input type="radio"/> traffic white RAL 9016 (UGR ≤ 22) | 7 |
| <input type="radio"/> matt silver (UGR ≤ 19)            | 4 |
| <input type="radio"/> jet black RAL 9005 (UGR ≤ 16)     | 1 |
| <input type="radio"/> gold dust RAL 260-M (UGR ≤ 19)    | 9 |

#### BEAM ANGLE

|                 |   |
|-----------------|---|
| spot 11°*       | S |
| medium 21°      | M |
| flood 42°       | F |
| wide flood 54°* | W |

\*not available for CWD

### Options on request

#### COLOR RENDERING INDEX

CRI ≥ 95, 2 SDCM

#### CONTROL

Casambi

#### POWER SUPPLY

DIM 1-10V

### Light distributions



wallwasher

wallwasher floor

**INSET POWER** is the current consumption excluding any ballast  
**LUMINOUS FLUX** value calculated for 3000K, CRI ≥ 90, colour white, flood 2700K -4%, 4000K +6%



### SASSO 60 round



#### ADJUSTABLE (↓ IP 40 | ↑ IP 20)

| INSET POWER       | LUMINOUS FLUX | ORDER CODE               |
|-------------------|---------------|--------------------------|
| 8.7W 36 Vf 250mA  | 873lm         | 0 4 8 - 2 6 2 2 :: 1 ▣ ▲ |
| 10.4W 35 Vf 300mA | CWD 796lm     | 0 4 8 - 2 6 2 2 E 1 ▣ ▲  |

#### DOWNLIGHT (↓ IP 40/44 | ↑ IP 20)

| INSET POWER       | LUMINOUS FLUX     | ORDER CODE               |
|-------------------|-------------------|--------------------------|
| 8.7W 36 Vf 250mA  | ↓ IP 44 900lm     | 0 4 8 - 2 6 0 2 :: 1 ▣ ▲ |
| 10.4W 35 Vf 300mA | ↓ IP 40 CWD 808lm | 0 4 8 - 2 6 0 2 E 1 ▣ ▲  |



#### WALLWASHER (IP 20)

| INSET POWER      | LUMINOUS FLUX | ORDER CODE               |
|------------------|---------------|--------------------------|
| 8.2W 27 Vf 300mA | 635lm         | 0 4 8 - 2 6 4 1 :: 1 ▣ ▲ |

#### WALLWASHER/FLOOR (IP 20)

| INSET POWER      | LUMINOUS FLUX | ORDER CODE               |
|------------------|---------------|--------------------------|
| 8.2W 27 Vf 300mA | 633lm         | 0 4 8 - 2 6 4 1 :: 1 ▣ W |

### Mounting accessories

#### TRIMLESS MOUNTING SET for plasterboard ceilings 12.5/15/25mm

| COLOUR                                      | ORDER CODE            |
|---|-----------------------|
| <input type="radio"/> traffic white RAL9016 | 0 4 8 - 2 6 9 6 1 1 7 |

#### MOUNTING SET WITH TRIM for intermediate ceilings 2-25mm

| TYPE    | COLOUR   | ORDER CODE            |
|---------|--|-----------------------|
| 1 lamp  | <input type="radio"/> white aluminium RAL 9006 | 0 4 8 - 2 6 9 6 3 1 G |
|         | <input type="radio"/> traffic white RAL 9016   | 0 4 8 - 2 6 9 6 3 1 7 |
|         | <input type="radio"/> jet black RAL 9005       | 0 4 8 - 2 6 9 6 3 1 8 |
| 2 lamps | <input type="radio"/> white aluminium RAL 9006 | 0 4 8 - 2 6 9 8 3 1 G |
|         | <input type="radio"/> traffic white RAL 9016   | 0 4 8 - 2 6 9 8 3 1 7 |
|         | <input type="radio"/> jet black RAL 9005       | 0 4 8 - 2 6 9 8 3 1 8 |

#### TRIMLESS MOUNTING SET for soft acoustic ceilings 25-40mm

| COLOUR                                       | ORDER CODE            |
|--|-----------------------|
| <input type="radio"/> signal white RAL 9003  | 0 4 8 - 2 6 9 6 1 9 7 |
| <input type="radio"/> traffic black RAL 9017 | 0 4 8 - 2 6 9 6 1 9 8 |

#### MOUNTING SET WITH TRIM for soft acoustic ceilings 25-40mm

| TYPE   | COLOUR                                       | ORDER CODE            |
|--------|--|-----------------------|
| 1 lamp | <input type="radio"/> signal white RAL 9003  | 0 4 8 - 2 6 9 6 3 9 7 |
|        | <input type="radio"/> traffic black RAL 9017 | 0 4 8 - 2 6 9 6 3 9 8 |

#### MOUNTING TOOL for soft acoustic ceilings

| TYPE     | COLOUR                                       | ORDER CODE            |
|----------|--|-----------------------|
| SASSO 60 | <input type="radio"/> traffic black RAL 9017 | 0 4 8 - 2 6 9 5 9 1 8 |

#### CONCRETE MOUNTING HOUSING

| TYPE                      | L-W-H (mm)  | ORDER CODE            |
|---------------------------|-------------|-----------------------|
| exposed concrete ceilings | 230-230-162 | 0 4 8 - 2 6 9 5 2 1 0 |
| primed concrete ceilings* | 614-307-120 | 0 4 8 - 2 6 9 5 1 1 0 |

\*order mounting set separately, not applicable for 2 lamps mounting set with trim

**Electrical accessories****SASSO 60****POWER SUPPLY** 220-240V AC, 50-60 Hz,  PC II

| <b>TYPE</b>      | <b>EFFICIENCY</b> | <b>L-W-H (mm)</b> | <b>ORDER CODE</b> |
|------------------|-------------------|-------------------|-------------------|
| 250 mA   non DIM | $\eta$ 85 %       | 65-39-20          | 0 0 2 - 9 0 7 4 2 |
| 250 mA   DALI-2  | $\eta$ 85 %       | 143-43-30         | 0 0 2 - 9 0 7 4 6 |
| 300 mA   non DIM | $\eta$ 85 %       | 85-40-22          | 0 0 2 - 9 0 7 7 1 |
| 300 mA   DALI-2  | $\eta$ 88 %       | 143-43-30         | 0 0 2 - 9 0 7 6 2 |

**DIN RAIL COMPONENTS**

| <b>TYPE</b>   | <b>W-H-D (mm)</b> | <b>ORDER CODE</b>     |
|---|-------------------|-----------------------|
| <b>POWER SUPPLY</b> 220-240V AC<br>160W   48V DC constant voltage   | 72-90-63          | 0 0 5 - 6 5 2 0 2 1 0 |
| <b>LED DRIVER</b> DALI-2 DT6 1-2 addr.<br>200-1050mA settable const. current<br>2 x 42W   48V DC   $U_{OUT}$ 10-40V | 36-88-59          | 0 0 5 - 6 1 2 1 0 3 0 |

for more details and components see catalog XAL 22, page 981