

## MIRA 150/200

recessed

EN Round or square luminaire housing in die-cast aluminium, available in 2 different sizes; with trim; suitable for ceiling thickness of 2-25 mm; surface powder coated; installation without tools using snap spring closure; lighting level recessed; completely homogeneously illuminated, satinised or microprismatic PMMA cover; energy-efficient LEDs with very good colour rendering; external converter for ceiling insertion

IT Corpo illuminante rotondo o quadrato in pressofusione di alluminio, due misure; con bordo perimetrale; per soffitti di spessore 2-25 mm; verniciatura a polvere; montaggio senza utensili con chiusura a molla a scatto; superficie di emissione arretrata; diffusore satinato o a microprismi in PMMA a illuminazione assolutamente omogenea; LED ad efficienza energetica con elevata resa cromatica; converter esterno da inserire nel soffitto

### Quickinfo

3000 K, 4000 K  
CRI ≥ 90, 3 SDCM  
up to 128 lm/W  
L80 @ 50 000 h  
non DIM, DALI-2  
IP20, IP54

### Types

MIRA round



MIRA square



### Colours



### Light distribution



direct



90 mm  
recess depth



weatherproof  
protection (IP54)

## Order options

<b>IP RATING</b>	<input type="radio"/>
IP20	0
IP54	8

<b>COLOUR TEMPERATURE</b>	<input type="checkbox"/>
3000K	5
4000K	6

<b>CONTROL</b>	<input type="checkbox"/>
non DIM	1
DALI-2	3

<b>MATERIAL COLOUR</b>	<input checked="" type="checkbox"/>
<input type="radio"/> pure white RAL 9010	7
<input checked="" type="radio"/> jet black RAL 9005	8

<b>LIGHT OPTIC COVER</b>	<input checked="" type="checkbox"/>
opal	O
microprismatic	P

## Options on request

<b>EMERGENCY LIGHT</b>	
1h accupack	
3h accupack	

<b>MOUNTING SET</b>	
exposed concrete mounting housing	

<b>COLOUR TEMPERATURE</b>	
2700 K	



## MIRA 150 round trim



### DOWNLIGHT

SYSTEM POWER	COLOUR TEMP.	LUM. FLUX	ORDER CODE
13 W	3000K	1510lm	<input type="checkbox"/> 52-9323 <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
18.6 W	4000K	1670lm	<input type="checkbox"/> 52-9324 <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
	3000K	2030lm	
	4000K	2240lm	



## MIRA 200 round trim



### DOWNLIGHT

SYSTEM POWER	COLOUR TEMP.	LUM. FLUX	ORDER CODE
27.9 W	3000K	3050lm	<input type="checkbox"/> 52-9423 <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
50 W	4000K	3360lm	<input type="checkbox"/> 52-9424 <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
	3000K	4830lm	
	4000K	5330lm	



## MIRA 150 square trim



### DOWNLIGHT

SYSTEM POWER	COLOUR TEMP.	LUM. FLUX	ORDER CODE
13 W	3000K	1510lm	<input type="checkbox"/> 52-9343 <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
18.6 W	4000K	1670lm	<input type="checkbox"/> 52-9344 <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
	3000K	2030lm	
	4000K	2240lm	



## MIRA 200 square trim




### DOWNLIGHT

SYSTEM POWER	COLOUR TEMP.	LUM. FLUX	ORDER CODE
27.9 W	3000K	3050lm	<input type="checkbox"/> 52-9443 <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
50 W	4000K	3360lm	<input type="checkbox"/> 52-9444 <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
	3000K	4830lm	
	4000K	5330lm	

## Accessories

### THROUGH WIRING CONNECTION BOX



TYPE	L-W-H (mm)	ORDER CODE
non DIM cable $\varnothing$ 4-12mm	105-58-30	005-2531110
DALI cable $\varnothing$ 4-12mm	105-58-30	005-2551110

not necessary for 49W versions, converter already has the option for through-wiring